www.ruijie.com.cn

+

```
Ruijie(config)#wlan-config 1 SSID-ALL \\          +ssid
Ruijie(config)#ap-group default
Ruijie(config-group)#interface -mapping 1 10 \\    wlan  vlan          AP
```

```
Ruijie(config)#wlan-config 1 SSID-Slot1
Ruijie(config)#wlan-config 2 SSID-Slot2
    ......
Ruijie(config)#wlan-config 24 SSID-Slot24
Ruijie(config)#ap-group default
Ruijie(config-group)#interface -mapping 1 10 radio 1
Ruijie(config-group)#interface -mapping 1 10 radio 2
Ruijie(config-group)#interface -mapping 2 10 radio 3
Ruijie(config-group)#interface -mapping 2 10 radio 4
    ......
Ruijie(config-group)#interface -mapping 24 10 radio 47
Ruijie(config-group)#interface -mapping 24 10 radio 48
```

+

```
Ruijie(config)#wlan-config 1 SSID-2.4G
Ruijie(config)#wlan-config 2 SSID-5.8G
Ruijie(config)#ap-group default
Ruijie(config-group)#interface-mapping 1 10 radio 802.11b \\802.11b 2.4G
2 10 radio 802.11a \\802.11a 5.8G
```

AP AP AP AP AP ssid, vlan

AP

AM 5528 AP AM 5528-Slot-3

Ruijie(config)#ap-config AM 5528 \\ AP

Ruijie(config-ap)#slot 3 AM 5528-Slot-3

AM 5528 AP

Ruijie(config)#ap-config AM 5528 \\ AP

Ruijie(config-ap)#reset slot 3

www.ruijie.com.cn

1) AM 5528 AP 6 149

show ap-config slot *ap-name* AP Radio ID

```
Ruijie(config)#ap-config AM5528
Ruijie(config-ap)#channel 6 radio 5
Ruijie(config-ap)#channel 149 radio 6
```

2) AM 5528 AP 2.4G 30% 5.8G 35%

```
Ruijie(config)#ap-config AM5528
Ruijie(config-ap)#power local 30 radio 802.11b
Ruijie(config-ap)#power local 35 radio 802.11a
```

802.11a 802.11b power chan-width response-rssi country ampdu-rts beacon rate

AP

AP AP

```
Ruijie(config )#ap-config AM5528
Ruijie(config -ap)# led on slot 1
```

AP AP

no led on

AP

AM 5532

AM 5528 (EP)&MAP 752 (T) VLAN

MAP 752 (T) ibeacon AC ibeacon uuid uuid major major minor minor radio slotid AP radio AP radio ibeacon ibeacon +

MAP 752 (T) + IOTP + DHCP OPTION 224 IOTP AP IOTP ibeacon IOTP IOTP AC ibeacon AP IOTP AC IOTP +

AP AP AM 5528 (EP) MAP 752 (T) AM 5528 (EP) AM 5528 MAP 752 (T)

www.ruijie.com.cn

www.ruijie.com.cn/service.aspx

support.ruijie.com.cn

webchat.ruijie.com.cn

4008-111-000